

## ACCESS CONTROL KEYPAD READER



### Product Features

- RFID proximity reader and controller, easy to install, easy to use, stable performance.
- Operating way: Card and Password.
- Keypad with backlight.
- Indication: LED and electronic buzzer.
- Wiegand 26 out/in (be used as wiegand reader to controller, connect extra reader).
- Suitable for all kinds of access control system.
- Built-in high-current output drive for the electric lock.
- External doorbell option on the panel.

### Technical Specifications

Model	F-K12
User Capacity	2000
Card Type	EM(ID) card 125KHz
Output Format	Wiegand 26 bits (default)
Open Mode	Card or card & password or password
Operating Voltage	DC12V
Operating Current	<60mA
Card Reading Distance	20~50mm
Backlight	Yes
IP Rating	IP65
Door Opening Time	0~99s (Adjustable)
Operating Temperature	-45°C~60°C
Operating Humidity	10%-90% RH
Dimensions	114×75×16(mm)

### Connection Details

